





Cut off the position marked by 1 and 2. We don't need the right side part of them.

Find out the B+, ACC and GND wire of original vehicle.

The yellow wire on the left part of 1 is connected to B+ wire of original vehicle.

The red wire on the left part of 1 is connected to ACC wire of original vehicle.

The black wire is connected to the GND wire of original vehicle.

Find out the AUX input line of the original car, the brown line on the left part of 2 is connected to the original car AUX-L, the blue is connected to AUX-R, the black line is connected to the original car GND line

The following figure is the ISO interface definition map

